







HV48100 DIP Switch and Pin Layout

1. DIP Switch

Brand	DIP Code	Picture	Brand	DIP Code	Picture
Afore	000000		Ingeteam	110000	
Deye	100000		KEHUA	001000	
Megarevo	010000		Solis	101000	

Notes: DIP code in the schematic represent DIP switches from left to right facing front panel.
Dialing up = " 1 ", Dialing down = " 0 ".

2. Pin Layout

PIN No.	Battery	Afore	Deye/Sol-Ark	Megarevo	Ingeteam	KEHUA	Solis
1		CAN_H	485_B			CAN_H(N)	
2			485_A			CAN_L(P)	
3		CAN_L				485_A(R)	
4	CAN_H		CAN_H	CAN_H	CAN_H	485_B(S)	CAN_H
5	CAN_L		CAN_L	CAN_L	CAN_L		CAN_L
6							
7	485_A		485_A	485_A			
8	485_B		485_B	485_B			